

MONITORING > TILTMETER NODE

## **ACKCIO TILTMETER NODE**

Code: N625



p to 50 nodes and 12 hops with AES-128 end-to-end encryption.

- The BEAM-TM operates autonomously using a high-capacity Li-SOCl₂ D-cell battery, delivering multi-year performance depending on sampling frequency and transmission settings.
- Configuration, setup, and data diagnostics are handled through Ackcio Nimbus, an Android application for quick deployment and network management.
- The IP67-rated aluminium enclosure provides superior environmental protection, making it ideal for long-term outdoor installations in challenging site conditions.
- Mounting options include both horizontal/vertical and rail mounting plates, designed for flexible installation and secure alignment in any orientation.

## **TECHNICAL SPECIFICATIONS**

- Sensor Type: Sisgeo self-compensated MEMS inclinometer
- Measurement Axes: Biaxial



• Measurement Range: ±15°

• Accuracy: ±0.003° (for ±2.5°, ±5.0°, ±10° ranges); ±0.01° (for ±15° range)

Resolution: 0.0001°

• Temperature Offset: ±0.003°/°C (-20 °C to +80 °C)

• Thermistor Range: −20 °C to +80 °C (3 kΩ sensor)

• Thermistor Resolution: 0.1 °C

Thermistor Accuracy: ±0.5 °C (0 °C to +50 °C)

• Radio Band: ISM 863-870 MHz / 902-928 MHz

• Transmit Power: Up to 1 W (30 dBm)

Modulation: 2-GFSK

Data Rate: 50 kbps

• Network Capacity: Up to 50 nodes, 12 hops

• Range: Up to 5 km (line-of-sight), 1 km (urban), 500 m (subsurface)

MCU: Arm® Cortex®-M3 48 MHz, 32-bit CPU

• Memory: 128 KB flash, 20 KB SRAM, 8 MB external flash

• Clock: High-precision RTC (10 ppm, -40 °C to +80 °C)

 Interfaces: USB 2.0 (Micro B, 5 V, 500 mA max), LED indicators (SYS, SENS), buttons (TEST, RESET, FORMAT)

• Operating Temperature: -40 °C to +80 °C

• Enclosure: Die-cast aluminium, IP67 rated

• Power Supply: 2.7–4 V DC internal battery

• Internal Battery: 1 × D-cell Li-SOCl<sub>2</sub> 3.6 V, 19 Ah

Typical Current Drain: <20 μA (idle), <100 mA (RX), <300 mA (TX)</li>

 Circuit Protection: Surge (60 V DC breakdown), impulse (500 V typical), reverse polarity, shortcircuit, ESD 15 kV

• Firmware: Ackcio Mesh low-power networking firmware

Software: Ackcio Nimbus Android setup and monitoring app



## **ORDERING INFORMATION**

will be added soon ...

## **OTHER PHOTOS**



